

AMENDMENTS TO THE CLAIMS

1. (Previously Presented) A high-voltage power supply, comprising:
 - a power scaling section receiving an input voltage signal and converting said input voltage signal to a controllable DC voltage;
 - a push-pull converter for converting said controllable DC voltage to a high-frequency wave; and
 - a voltage multiplier receiving said high-frequency wave generated by said push-pull converter and performing successive voltage doubling operations to generate a high-voltage DC output, the generated high-voltage DC output being varied as said controllable DC voltage varies.
2. (Original) The high-voltage power supply of claim 1, further comprising:
 - a control module for controlling said power scaling section and said push-pull converter.
3. (Original) The high-voltage power supply according to claim 2, wherein
 - said power scaling section includes a switching element, a duty cycle of which controls the amplitude of said controllable DC voltage, and
 - said control module outputs a gate switching signal to said switching element of said power scaling section as a function of a desired output voltage of the high-voltage power supply.
4. (Original) The high-voltage power supply according to claim 3, wherein said control module receives a feedback signal based on the output of said power scaling section to adjust said gate switching signal.

5. (Original) The high-voltage power supply according to claim 2, wherein said push-pull converter includes a plurality of switching elements and a transformer for generating said high-frequency wave, and said control module outputs gate switching signals to the switching elements of said push-pull converter to control the frequency of said high-frequency wave.
6. (Original) The high-voltage power supply according to claim 5, wherein said switching elements are MOSFET switching elements.
7. (Original) The high-voltage power supply according to claim 1, wherein said high-frequency wave is a square wave.
8. (Original) The high-voltage power supply according to claim 1, wherein the frequency of said high-frequency wave is approximately 100 kHz.
9. (Previously Presented) The high-voltage power supply according to claim 1, wherein said controllable DC voltage is in the range of approximately 0-to-28 V.
10. (Original) The high-voltage power supply according to claim 1, wherein said power supply generates an output voltage of in the range of approximately 0-to-30 kV, DC.
11. (Original) The high-voltage power supply according to claim 1, wherein said high-frequency wave has an amplitude of approximately 0-to-1 kV.
12. (Original) The high-voltage power supply according to claim 2, wherein said control module is an analog controller.

13. (Original) The high-voltage power supply according to claim 1, wherein said voltage multiplier includes a plurality of voltage doubler stages on a circuit board and said high-voltage power supply further comprises an insulation system associated with said circuit board.
14. (Original) The high-voltage power supply according to claim 13, wherein said insulation system is a multi-layer system of n layers of insulation and m conducting strips positioned between successive insulating layers.
15. (Original) The high-voltage power supply according to claim 13, wherein said insulation system is a field-controlled multi-layer insulation system.
16. (Original) The high-voltage power supply according to claim 13, wherein said plurality of voltage doubler stages are divided among multiple circuit boards, separate from said power scaling section and said push-pull converter.
17. (Previously Presented) The high-voltage power supply according to claim 13, wherein said plurality of voltage doubler stages include capacitors arranged in a pattern in which adjacent capacitors are non-parallel, so as to diverge on one end.
18. (Previously Presented) A method for providing high-voltage power, comprising:
receiving an input voltage signal and scaling said input voltage signal to a controllable DC voltage;
converting said controllable DC voltage to a high-frequency wave; and

performing voltage multiplication on said high-frequency wave generated by said converting step to generate a high-voltage DC output, the generated high-voltage DC output being varied as said controllable DC voltage varies.

19. (Original) The method of claim 18, further comprising:

controlling said scaling and converting steps in accordance with a command signal.

20. (Original) The method according to claim 19, wherein

said scaling step is performed by a power scaling section having a switching element, a duty cycle of which controls the amplitude of said controllable DC voltage, and

said step of controlling outputs a gate switching signal to the switching element of the power scaling section as a function of a desired output voltage.

21. (Original) The method claim 20, wherein said controlling step generates said gate switching signal as a function of a feedback signal indicating the output of the power scaling section.

22. (Original) The method according to claim 19, wherein

said converting step is performed by push-pull converter that includes a plurality of switching elements and a transformer for generating said high-frequency wave, and

said controlling step outputs a gate switching signal to the switching elements of said push-pull converter to control the frequency of said high-frequency wave.

23. (Original) The method according to claim 22, wherein said switching elements are MOSFET switching elements.
24. (Original) The method according to claim 18, wherein said high-frequency wave is a square wave.
25. (Original) The method according to claim 18, wherein the frequency of said high-frequency wave is approximately 100 kHz.
26. (Previously Presented) The method according to claim 18, wherein said controllable DC voltage is in the range of approximately 0-to-28 V.
27. (Original) The method according to claim 18, wherein said method generates an output voltage of approximately 0-to-30 kV, DC.
28. (Original) The method according to claim 18, wherein said high-frequency wave has an amplitude of 0-to-1 kV.
29. (Previously Presented) The high-voltage power supply according to claim 1, wherein the frequency of said high-frequency wave is greater than approximately 20 kHz.
30. (Previously Presented) The method according to claim 18, wherein the frequency of said high-frequency wave is greater than approximately 20 kHz.
31. (New) A high-voltage power supply, comprising:

a power scaling section receiving an input voltage signal and converting said input voltage signal to a controllable DC voltage;

a push-pull converter for converting said controllable DC voltage to a high-frequency wave, said high-frequency wave having a frequency greater than approximately 20 kHz; and

a voltage multiplier receiving said high-frequency wave generated by said push-pull converter and performing successive voltage doubling operations to generate a high-voltage DC output, the generated high-voltage DC output being varied as said controllable DC voltage varies so as to output various desired output voltage levels in a range that includes voltages up to approximately 30kV.